

AMENDMENTS TO THE CLAIMS

Claim 1. (Canceled)

2. (Currently amended) ~~The step-up/down DC-DC converter as claimed in claim 1,~~
~~wherein the control part further comprises:~~ A step-up/down DC-DC converter, comprising:

a voltage step-up/down part configured to generate and output a predetermined output voltage by stepping up or down an input voltage in accordance with a control signal input to the voltage step-up/down part; and

a control part configured to generate an error signal indicating an error between a voltage value obtained by dividing the output voltage and a predetermined reference voltage, compare the error signal and first and second triangle wave signals, and cause the voltage step-up/down part to perform a step-up or step-down operation based on a result of the comparison,

wherein the control part includes:

a first triangle wave generator circuit configured to generate the first triangle wave signal compared with the error signal to determine whether to cause the voltage step-up/down part to perform the step-down operation;

a second triangle wave generator circuit configured to generate the second triangle wave signal compared with the error signal to determine whether to cause the voltage step-up/down part to perform the step-up operation;

a first voltage generator circuit configured to generate and output a first voltage V_a for setting a lower limit voltage of the first triangle wave signal;

a second voltage generator circuit configured to generate and output a second voltage V_b for setting an upper limit voltage of the first triangle wave signal;

a third voltage generator circuit configured to generate and output a third voltage V_c for setting an upper limit voltage of the second triangle wave signal; and

a current generator circuit configured to generate and output a current setting a slope of voltage variation of each of the first and second triangle wave signals,

wherein the first triangle wave generator circuit is configured to generate a clock signal synchronized with the generated first triangle wave signal, and output the generated clock signal to the second triangle wave generator circuit, the second triangle wave generator circuit is configured to generate the second triangle wave signal synchronized with the first triangle wave signal based on the input clock signal, and output the second triangle wave signal, the first triangle wave generator circuit is being configured to generate the first triangle wave signal from the first and second voltages V_a and V_b and the current output from the current generator circuit, and the second triangle wave generator circuit is being configured to generate the second triangle wave-signal from the third voltage V_c , the current output from the current generator circuit, and the clock signal output from the first triangle wave generator circuit.

3. (Original) The step-up/down DC-DC converter as claimed in claim 2, wherein the first, second, and third voltage generator circuits are configured to generate and output the corresponding first, second, and third voltages V_a , V_b , and V_c so that the first, second, and third voltages V_a , V_b , and V_c satisfy $V_a < V_b < V_c$ and $(V_b - V_a) > (V_c - V_b)$.

4. (Original) The step-up/down DC-DC converter as claimed in claim 2, wherein the second triangle wave generator circuit is configured to decrease a voltage of the second triangle wave signal when the voltage of the second triangle wave signal reaches the third voltage V_c , and increase the voltage of the second triangle wave signal in synchronization with the clock signal.

5. (Original) The step-up/down DC-DC converter as claimed in claim 2, wherein

each of the first, second, and third voltage generator circuits is configured to generate a corresponding one of the first, second, and third voltages V_a , V_b , and V_c by dividing a predetermined voltage by resistors.

Claims 6-7. (Canceled)

8. (Currently amended) ~~The step-up/down DC-DC converter as claimed in claim 7, wherein the control part further comprises:~~ A step-up/down DC-DC converter, comprising:

a voltage step-up/down part configured to generate and output a predetermined output voltage by stepping up or down an input voltage in accordance with a control signal input to the voltage step-up/down part; and

a control part configured to generate an error signal indicating an error between a voltage value obtained by dividing the output voltage and a predetermined reference voltage, compare the error signal and first and second triangle wave signals, and cause the voltage step-up/down part to perform a step-up or step-down operation based on a result of the comparison,

wherein the control part includes:

a first triangle wave generator circuit configured to generate the first triangle wave signal compared with the error signal to determine whether to cause the voltage step-up/down part to perform the step-down operation;

a second triangle wave generator circuit configured to generate the second triangle wave signal compared with the error signal to determine whether to cause the voltage step-up/down part to perform the step-up operation;

a first voltage generator circuit configured to generate and output a first voltage V_a for setting a lower limit voltage of the first triangle wave signal;

a second voltage generator circuit configured to generate and output a second voltage V_b for setting a lower limit voltage of the second triangle wave signal;

a third voltage generator circuit configured to generate and output a third voltage V_c for setting an upper limit voltage of the second triangle wave signal; and

a current generator circuit configured to generate and output a current setting a slope of voltage variation of each of the first and second triangle wave signals,

wherein the second triangle wave generator circuit is configured to generate a clock signal synchronized with the generated second triangle wave signal, and output the generated clock signal to the first triangle wave generator circuit, the first triangle wave generator circuit is configured to generate the first triangle wave signal synchronized with the second triangle wave signal based on the input clock signal, and output the first triangle wave signal, the first triangle wave generator circuit being is configured to generate the first triangle wave signal from the first voltage V_a , the current output from the current generator circuit, and the clock signal output from the second triangle wave generator circuit, and the second triangle wave generator circuit being is configured to generate the second triangle wave signal from the second and third voltages V_b and V_c and the current output from the current generator circuit.

9. (Original) The step-up/down DC-DC converter as claimed in claim 8, wherein the first, second, and third voltage generator circuits are configured to generate and output the corresponding first, second, and third voltages V_a , V_b , and V_c so that the first, second, and third voltages V_a , V_b , and V_c satisfy $V_a < V_b < V_c$ and $(V_b - V_a) < (V_c - V_b)$.

10. (Original) The step-up/down DC-DC converter as claimed in claim 8, wherein the first triangle wave generator circuit is configured to increase a voltage of the first triangle wave signal when the voltage of the first triangle wave signal reaches the first voltage V_a , and decrease the voltage of the first triangle wave signal in synchronization with the clock signal.

11. (Original) The step-up/down DC-DC converter as claimed in claim 8, wherein each of the first, second, and third voltage generator circuits is configured to generate a

corresponding one of the first, second, and third voltages V_a , V_b , and V_c by dividing a predetermined voltage by resistors.

Claims 12-14. (Canceled)